


Raspberry Pi[®]

Hardware Projects

Volume 1



Andrew Robinson
Mike Cook

WILEY

Raspberry Pi[®] Hardware Projects

Volume 1

Andrew Robinson and Mike Cook
A John Wiley & Sons, Ltd, Publication

WILEY

Raspberry Pi® Hardware Projects, Volume 1

This edition first published 2013

© 2013 John Wiley & Sons, Ltd.

Registered office

John Wiley & Sons Ltd, The Atrium, Southern Gate,
Chichester, West Sussex, PO19 8SQ, United Kingdom

For details of our global editorial offices, for customer services and for information about how to apply for permission to reuse the copyright material in this book please see our website at www.wiley.com.

The right of the authors to be identified as the authors of this work has been asserted in accordance with the Copyright, Designs and Patents Act 1988.

All rights reserved. No part of this publication may be reproduced, stored in a retrieval system, or transmitted, in any form or by any means, electronic, mechanical, photocopying, recording or otherwise, except as permitted by the UK Copyright, Designs and Patents Act 1988, without the prior permission of the publisher.

Wiley also publishes its books in a variety of electronic formats. Some content that appears in print may not be available in electronic books.

Designations used by companies to distinguish their products are often claimed as trademarks. All brand names and product names used in this book are trade names, service marks, trademarks or registered trademarks of their respective owners. The publisher is

not associated with any product or vendor mentioned in this book. This publication is designed to provide accurate and authoritative information in regard to the subject matter covered. It is sold on the understanding that the publisher is not engaged in rendering professional services. If professional advice or other expert assistance is required, the services of a competent professional should be sought.

Trademarks: Wiley and the Wiley logo are trademarks or registered trademarks of John Wiley and Sons, Inc. and/ or its affiliates in the United States and/or other countries, and may not be used without written permission. Raspberry Pi is a trademark of the Raspberry Pi Foundation. All other trademarks are the property of their respective owners. John Wiley & Sons, Ltd. is not associated with any product or vendor mentioned in the book.

A catalogue record for this book is available from the British Library.

ISBN 978-1-118-58894-9 (ePub); ISBN 978-1-118-72391-3 (ePDF)

Table of Contents

[Introduction](#)

[Chapter 1: Test Your Reactions](#)

[Welcome to the Embedded World!](#)

[Good Practice](#)

[Obtaining Components](#)

[An Interface Board](#)

[PiFace Digital](#)

[Setting up PiFace Digital](#)

[Installing PiFace Digital Software](#)

[Connecting PiFace Digital](#)

[Using the Emulator](#)

[Interfacing with Python](#)

[Turning a Light On](#)

[Reading a Switch](#)

[The Reaction Timer](#)

[Meet PiFace Digital's Connectors](#)

[Connecting a Switch and an LED](#)

[Playing with the Reaction Timer](#)

[What Will You Interface?](#)

[Chapter 2: The Twittering Toy](#)

[Hacking the Toy](#)

[Building the Chicken](#)

[Wiring](#)

[Making It Talk](#)

[Using Espeak in Python](#)

[Testing the Espeak module](#)

[Making It Move](#)

[Creating Classes](#)

[Creating Objects](#)

[Testing As You Go](#)

[Connecting to Twitter](#)

[Building and Installing Python Modules](#)

[Talking to Twitter](#)

[Putting It All Together](#)

[Wrapping Up](#)

[More Ideas](#)

[Chapter 3: Disco Lights](#)

[Defining Your Sequence](#)

[Getting the Code to Do More](#)

[A Small Detour into Theory](#)

[Designing the Sequencer](#)

[Implementing the Sequencer](#)

[The Lights](#)

[Using Longer Strip Lights](#)

[Making the Lights Move](#)

[Designing the Circuit](#)

[Building the Circuit](#)

[Running the Circuit](#)

[Over to You](#)

[Appendix A: Getting Your Raspberry Pi Up and Running](#)

[Getting the OS on an SD Card](#)

[Connecting a Display](#)

[Connecting to a Network](#)

[Bootting the Operating System](#)

[Powering Up!](#)

[Common Problems](#)

[If You Need More Help](#)

[Appendix B: Introductory Software Project: The Insult Generator](#)

[Variables](#)

[Strings](#)

[Lists](#)

[Functions](#)

[Conditional Behaviour](#)

[Making Your Own Functions](#)

[Creating Loops](#)

[More Raspberry Pi Resources](#)

Some of the people who helped bring this book to market include the following:

Editorial and Production

**VP Consumer and Technology Publishing
Director**

Michelle Leete

**Associate Director-Book Content
Management**

Martin Tribe

Associate Publisher

Chris Webb

Executive Commissioning Editor

Craig Smith

Assistant Editor

Ellie Scott

Project Editors

Dana Lesh, Kathryn Duggan

Copy Editors

Dana Lesh, Kathryn Duggan

Technical Editor

Genevieve Smith-Nunes

Editorial Manager

Jodi Jensen

Senior Project Editor

Sara Shlaer

Editorial Assistant

Leslie Saxman

Marketing

Associate Marketing Director

Louise Breinholt

Marketing Manager

Lorna Mein

Senior Marketing Executive

Kate Parrett

Composition Services

Compositors

Carrie A. Cesavice, Jennifer Goldsmith

Proofreaders

Melissa Cossell, Dwight Ramsey

Introduction

You've got a Raspberry Pi – now what? This book has the answer; it's packed full of fun Raspberry Pi projects to inspire you. From getting your Pi generating comedy insults, testing your reactions and building a talking animatronic toy that tweets to building your own disco light show, prepare to be entertained and amazed by your credit card-sized computer.

One word of warning: After you start you might never stop! Electronics and coding can be addictive; who knows what you might go on to make with the skills you learn from this book.

[Appendix A](#), “Getting Your Raspberry Pi Up and Running”, is a beginner's guide to your first steps with the Raspberry Pi. If you've never coded before, [Appendix B](#), “Introductory Software Project: The Insult Generator”, will get you started programming in Python. [Chapter 1](#), “Test Your Reactions”, will get you wiring up simple computer-controlled circuits. [Chapter 2](#), “The Twittering Toy”, will show you how to make your code talk to Twitter and get you hacking household items. [Chapter 3](#), “Disco Lights”, shows you how to control LED strips and make them dance in time to the music. Along the way you will pick up the skills you need to develop your own ideas to make projects work exactly how you want them to.

Building and making is incredibly rewarding and satisfying. We want to get more people of the world to become producers of technology rather than consumers. The projects in this book are starting points – step by step, they're easy to follow so you can get results quickly. But

then the real satisfaction can come, that which comes from making the project your own. At the end of each chapter there are ideas and suggestions to extend the project, together with background information to point you in the right direction. The real addictive fun begins when you see your own ideas become reality.

Welcome to the world of digital making.

Chapter 1

Test Your Reactions

In This Chapter

- Getting started interfacing hardware with the Raspberry Pi
- Working with basic electronic circuits
- An introduction to electronic components, including transistors and resistors
- How to wire up a switch and an LED

Think you've got fast fingers? Find out in this chapter as you take your first steps in hardware interfacing to build a reaction timer. You'll program the Raspberry Pi to wait a random time before turning on a light and starting a timer. The timer will stop when you press a button.

Welcome to the Embedded World!

For some people the idea that computers aren't always big black or beige boxes on desks is a surprise, but in reality the majority of computers in the world are embedded in devices. Think about your washing machine – to wash your clothes it needs to coordinate turning the water on, keeping it heated to the right temperature, agitating your clothes by periodically spinning the drum, and emptying the water. It might repeat some of these steps multiple times during a

wash, and has different cycles for different types of fabric. You might not have realised it's a computer program. It takes inputs from switches to select the wash and sensors that measure water temperature, and has outputs that heat the water and lock the door shut, and motors to turn the drum and open and close valves to let water in and out.

YOUR TURN!

Take a moment to consider the number of appliances and gadgets that need to measure inputs, do some processing to reach a decision and then control an output in response.

A modern kitchen is crammed with computers that watch over and automate our appliances to save us effort. Computers aren't just embedded in practical products either; they're in electronic toys and entertainment devices. After working through this chapter and the other examples in this book you'll be on your way to designing your own embedded systems to make your life easier, or entertain you.

Before you get too carried away connecting things up it's worth considering a couple of warnings that will protect you and your electronic components.

Good Practice

Electricity can be dangerous, so it is important to use it safely. The muscles in your body are controlled by tiny electrical signals, and these can be affected if electricity flows through your body. Your heart is a muscle that can be stopped by an electric shock.

The flow of electricity can cause heating, which will either cause burns to your body (sometimes deep within tissue) or can cause a fire.

WARNING

Electricity can kill! Only experiment with low voltages and currents, and never work with mains. If you are ever in doubt then you should check with someone suitably qualified.

Hardware is less forgiving than software; if you make a mistake with code, you might get an error, the program might crash, or in rare cases you might cause your Raspberry to reset. If you make a mistake in hardware then you can cause permanent damage. As such, hardware engineers tend to check and double check their work before applying the power!

When experimenting you should beware of short-circuiting your projects. Make sure that nothing conductive touches your circuit. Tools, metal watchstraps and jewellery, unused wires, spare components and tin foil have all been known to damage circuits. Keep your working area clear of anything you don't need and make sure that nothing metallic can touch your Raspberry Pi or circuit.

Static Discharge

You may have felt a small electric shock due to static sometimes. This occurs when a charge builds up and then discharges to a conductor, which you feel as a small shock. If you are holding a component when this happens, that large voltage will flow through the component and damage it. Other objects such as plastic can become charged too and then discharge through a component. As such, you should take care to avoid this static discharge through components or circuits. In industry, conductive work surfaces and wrist straps are earthed to prevent static buildup. This may be an extreme solution for a hobby; you can discharge yourself by touching something earthed like a water tap, and avoid working on surfaces that are prone to

picking up static charge like plastics – for example, avoid working on nylon carpets or plastic bags.

TIP

You may have noticed components are supplied in antistatic bags, or static-dissipative bags or static-barrier bags. These bags are made from special plastic designed to protect the contents from being zapped by static discharges and conduct any charge away. Beware that some of these bags can be slightly conductive and so may interact with your powered-up circuit.

Obtaining Components

Another difference with hardware is that you can't download everything you need from the Internet! However, you can do the next best thing and order parts online. There are a number of online electronics retailers that supply parts, including the two worldwide distributors of the Raspberry Pi, element14/Premier Farnell/Newark and RS Components. Pimoroni, SparkFun, SK Pang, Cool Components, Adafruit and other web stores have a smaller range but cater well to electronic hobbyists.

Maplin Electronics and Radio Shack have shops on the high street with a smaller selection of parts.

An Interface Board

Although the Raspberry Pi has a general purpose input/output (GPIO) connector that you can connect to directly, as a beginner, it is easier to use an add-on board. An interface board can offer some protection to your Pi against burning out if you get your wires crossed!

PiFace Digital